

MaximalRDV Series

Rack Access Power Controllers (PTC)



Maximal Rack Mount Series units distribute and switch power to access control systems and accessories. They convert a 220VAC 50/60Hz input into eight (8) or sixteen (16) independently controlled 12VDC and/or 24VDC PTC protected outputs. Outputs are activated by an normally open (NO) or normally closed (NC) dry trigger input from an Access Control System, Card Reader, Keypad, Push Button, PIR, etc. Units will route power to a variety of access control hardware devices including: Mag Locks, Electric Strikes, Magnetic Door Holders, etc. Outputs will operate in both Fail-Safe and/or Fail-Secure modes. The FACP Interface enables Emergency Egress, Alarm Monitoring, or may be used to trigger other auxiliary devices. The fire alarm disconnect feature is individually selectable for any or all of the outputs.



Maximal3RHDV

Key Features

- Eight (8) or Sixteen (16) independently controlled PTC protected 12VDC and/or 24VDC outputs
- Individually selectable Mag Lock/Strike (Fail-Safe, Fail-Secure) solid state PTC protected outputs
- Thermal and short circuit protection with auto reset
- Supervision:
 - AC Fail
 - Low Battery
- Fire Alarm disconnect (latching or non-latching) is individually selectable for any or all of the outputs
- Fire Alarm disconnect input options:
 - a) Normally open (NO) or normally closed (NC) dry contact input
 - b) Polarity reversal input from FACP signaling circuit
- Built-in charger for sealed lead acid or gel type batteries
- Instantaneous transfer to stand-by batteries
- Lifetime Warranty

MaximalRDV Power Supply Series Configuration Reference Chart

Altronix Model Number	Power Supply 1 (8 outputs)	Power Supply 2 (8 outputs)	Total Output Current	PTC Protected Auto-Resettable Outputs	Maximum Current Per ACM8CBBR-M Output	220VAC 50/60Hz Input Current	Power Supply Board Input Fuse Rating
Maximal1RHDV	12VDC @ 4A	N/A	4A	8	2.0A	0.9A	5A/250V
	24VDC @ 3A	N/A	3A				
Maximal1RDV	12VDC @ 4A	N/A	4A	16	2.0A	0.9A	5A/250V
	24VDC @ 3A	N/A	3A				
Maximal3RHDV	12VDC @ 6A	N/A	6A	8	2.0A	0.9A	3.5A/250V
	24VDC @ 6A	N/A					
Maximal3RDV	12VDC @ 6A	N/A	6A	16	2.0A	0.9A	3.5A/250V
	24VDC @ 6A						
Maximal33RDV	12VDC @ 6A	12VDC @ 6A	12A	16	2.0A	1.9A	3.5A/250V
	24VDC @ 6A	24VDC @ 6A					
	12VDC @ 6A	24VDC @ 6A					

Lifetime Warranty

MaximalRDV Series

Rack Access Power Controllers (PTC)



Specifications

Input

Voltage 220VAC (working range 198VAC - 256VAC), 50/60Hz

Fusing Varies, See Reference Chart

Outputs

Voltage 12VDC and/or 24VDC, see Reference Chart

Current Varies, see Reference Chart

Protection PTC 2.0A

Other Overvoltage protection
Filtered and regulated outputs

Back-up Battery *(separate enclosure is required)*

Type Sealed lead acid or gel type

Charging current 0.7A

Fuse Rating 15A @ 32VDC
(Maximal1RHDV and Maximal1RDV);
Maximal3RHDV, Maximal3RDV,
and Maximal33RDV do not have a battery fuse

Failover Upon AC loss, instantaneous

Fire Alarm Disconnect

Supervised Latching or non-latching, individually selectable for any or all of the outputs.

Supervision

AC Failure Form "C" contacts

Battery Form "C" contacts

Indicators (LED)

Input Illuminated ON/Reset Switch

Output Individual Output Status LEDs located on the front panel

Physical and Environmental

Dimensions (H x W x D)

3.25" x 19.125" x 8.5" (82.55mm x 485.78mm x 215.9mm)

Weight (approx.)

Model	Product Weight	Shipping Weight
Maximal1RHDV	10.7 lb. (4.85 kg)	12.7 lb. (5.76kg)
Maximal1RDV	10.7 lb. (4.85 kg)	12.7 lb. (5.76kg)
Maximal3RHDV	10.85 lb. (4.92 kg)	12.85 lb. (5.83 kg)
Maximal3RDV	10.85 lb. (4.92 kg)	12.85 lb. (5.83 kg)
Maximal33RDV	12.4 lb. (5.62 kg)	14.3 lb. (6.49 kg)

Temperature

Operating 0°C to 49°C (32°F to 120°F)

Storage -20°C to 70°C (-4°F to 158°F)

Relative Humidity 85% +/-5%

BTU/Hr. (approx.):

Model	12VDC	24VDC	12 and 24VDC
Maximal1RHDV	25	37	N/A
Maximal1RDV	25	37	N/A
Maximal3RHDV	37	74	N/A
Maximal3RDV	37	74	N/A
Maximal33RDV	74	141	106

Accessories (order separately)



RE2

RE2 - Rack Mount Battery Enclosure
accommodates up to four (4) 12VDC/7AH batteries

Lifetime Warranty