

Features

- Call-placed indicator
- Call cancellation only at point of origin
- Flame retardant (UL® 94V-0) plastic faceplate
- Contacts to signal dome light, and buzzer or bell

Description

The SF118C Emergency Switch is available in two models. Both models feature a rugged, long-life, positive-acting switch mounted on a flame retardant (UL® 94V-0) plastic faceplate marked **EMERGENCY** that includes a red LED. Signaling an emergency requires just a short pull in any direction on the 6' long nylon cord. The signal cannot be canceled except at the point of origin. The SF118/2C provides two contacts, one to signal a dome light and master station, and one to signal a buzzer or DC bell. The SF118/4C provides two additional contacts that may be used to operate additional signaling devices as needed.

Specifications

| | |
|--------------------|--|
| Dimensions: | 4.5"H × 2.75"W × 1.5"D (114 mm × 70 mm × 38 mm) |
| Switch: | SF118/2C: PDT SF118/4C: PDT |
| Construction: | Switch and lamp are mounted to a flame retardant (UL® 94V-0) plastic faceplate |
| Call-Placed Light: | Red LED |
| Connections: | Wire leads |
| Mounting: | Standard single-gang electrical box |



SF118/2C, SF118/4C Emergency Call Station

Required Components

CM800 Emergency Call System