

SAFEPATH Mass Notification System (SPMNS)



SP40S



SPB-320

SPB-80/4
SPB-160



PS-8-LP



SPMNS-MIC



SP4Z-A/B

Contents

Description

	Page
SPMNS	2-4
SPMNS-MIC	3
Expansion Options	
SAFEPATH 2-zone Class A or 4-zone Class B speaker audio splitter.....	5
SAFEPATH audio boosters.....	6-7
Architects and engineers specifications	8-9



Powering Business Worldwide

SAFEPATH Mass Notification: SPMNS

Description

Eaton's SAFEPATH MNS (SPMNS) is an In-Building Mass Notification System for fire alarm, emergency communications and voice evacuation with 24 VDC battery back up. It provides personnel and building occupants with clear, concise and intelligible voice messages that communicate how people should respond to a variety of emergency situations.

The SPMNS, which meets UL 2572 requirements for MNS, interfaces with a building fire alarm system (FAS) to provide a complete In-Building MNS. An integral part of the fire system, the SPMNS controls all audio and visual notification appliances for both fire and MNS and reports trouble and supervisory signal through the FAS. Supervised voice speakers controlled by the SPMNS can be used for both fire and emergency communication applications.

The SPMNS single channel system is capable of delivering 40 watts of supervised high fidelity audio power and 2 amps of supervised 24 VDC synchronized strobe power. It comes standard with an on-board digital voice messaging system with 8 standard messages, a hand-held microphone for fire messages, power supply/battery charger and numerous additional features. A dedicated MNS microphone (SPMNS-MIC) will be utilized for live voice messages for emergency communications. The SAFEPATH system is expandable to 5280 watts utilizing the SPB-80/4 (80 watts and 4 amps of strobe power), the SPB-160 (160 watts) or SPB-320 (320 watts) supervised audio power boosters. All models available in 115 VAC or 220 VAC.

Features

Approvals & Compliance

- Approvals: UL 2572 for MNS, UL Standard 864, 9th edition, UL Standard 1711
- OSHA 1910.165 and ADA Compliant
- Year Warranty

Voice messages

- Complies to NFPA-72 requirements
- Supervised NAC speaker and strobe circuits
- Live microphone override
- 5 digitally pre-recorded MNS voice messages
- 3 digitally pre-recorded fire voice messages
- User selectable pre-tones for fire messages
- Flexible, field-programmable messaging capabilities

Strobe inputs and activation

- 2 Amps of 24 VDC supervised strobe power with built-in Wheelock sync protocol. Power limited.
- Strobe output is selectable for control of Wheelock sync protocol or non-sync operation
- Strobe terminals have pass-through capability for Wheelock sync or non-sync operation
- 24 VDC supervised and synchronized strobe power can be expanded to meet the requirements of the installation via connecting to optional Wheelock power boosters

Speaker output

- 40 watts of supervised audio power

- Speaker outputs: 25V or 70.7V power limited

Audio processing

- Connectivity of optional speaker splitter modules
- Dual-tone tone generator with Code 3 Tone and Slow Whoop for alerting of system trouble
- Night ringer/security alerting capability
- Audio power can be expanded by connecting to optional audio power boosters
 - SPB-80/4: 80-watt supervised audio power booster with 4 Amp of Synchronized Strobe Power
 - SPB-160: 160-watt supervised audio power booster
 - SPB-320: 320-watt supervised audio power booster

Live & pre-recorded message announcement

- Supplied with 8 pre-recorded emergency messages
- Capable of in-field recording of all messages via 1/8" line level audio input jack
- On board push-to-talk microphone
- Dedicated MNS microphone

System Activation

- Contact closure message activation

Note: Please read these specifications and associated installation instructions, before using, specifying, or installing this product. Visit Eaton.com/massnotification for current installation instructions.

Note: Benefits & advantages

- One Supervised, Multi-Function, Voice Fire Alarm/Emergency Communications System
- Interfaces with addressable FAS
- Interfaces with telephone system for general paging requirements
- Built-in power for visual notification appliances (e.g., strobes)
- Controls audio and visual notification appliances for both fire and MNS
- Voice speakers can be used for both fire and emergency communication applications
- Reports trouble and supervisory signal for both the FAS and MNS

Applications

- **Multi-use applications:** The system can function as an evacuation system, an emergency messaging system, and an employee notification system
- **Fire code applications:** The system is listed under UL 2572 for MNS, UL Standard 864, 9th edition delivering supervised audio and voice messaging with strobes and notification appliance circuits (NAC) for visual alerting
- **Economic OSHA applications:** The system is OSHA 1910.165 compliant and therefore it **does not** require reliability inspections every two months or the required spare parts inventory.
- Wide ranging applications—from small to large facilities

Installation & maintenance

- Multiple trouble LED indicators for quick system diagnostics
- Fully supervised circuitry always in effect (via patent pending technology)
- Removable quick connect/disconnect terminals for ease of wiring; accepts #12 to #22 AWG
- Power-limited circuitry with Class "B" or Class "A" wiring

(Class "A" only with use of audio splitter)

- Surge protected circuitry

Power Supply & Batteries

- 24 VDC, 33AH Max rechargeable battery back-up power circuitry built-in
- Batteries can be housed in the enclosure (Up to two BAT-1212, 12 volt, 12 ampere hour batteries can fit in the enclosure). Actual battery size required will depend on speaker and/or strobe load. Batteries are sold separately.

Voice Message Priority

The SPMNS will override the FAS with live voice from a separate MNS microphone or manual activation of a high-priority emergency message. After the SPMNS relinquishes control, the following occurs:

1. Without an active fire alarm signal, the fire alarm system shall automatically restore to normal operation
2. With an active fire alarm signal, the fire alarm shall operate based on the Emergency Response Plan (ERP)

The fire alarm signal deactivation function occurs only when both the FAS is in alarm condition and an MNS voice message is initiated by the SPMNS. When the fire alarm notification is overridden by the SPMNS priority emergency message, all other features of the FAS remain unaffected.

Priority messaging is as follows:

- Live voice messages from the MNS microphone
- Pre-recorded prioritized mass notification messages
- Live voice messages from the fire microphone
- Pre-recorded fire messages

SPMNS Microphone

Description

SPMNS-Mic is used with the SPMNS.



Features

- Approvals: UL 2572 for MNS, UL Standard 864, 9th edition and California State Fire Marshal (CSFM)
- UFC 04-021-01 Compliant
- Supervised hand held push to talk microphone
- Key required to enable microphone use
- Individual front panel LED indication for; System Normal, System Trouble and Alarm
- When used with the SPMNS, the priority level of the SPMNS-MIC is 1, the SPMNS on-board fire microphone is a lower priority
- Voice frequency response: 275 Hz - 6.5 kHz
- Requires 24VDC, supplied by the SPMNS, Audio Boosters, or SP4-RMX
- Input current: Standby: 23mA; Alarm: 30mA
- Audio output level: 1.05V RMS
- 6 wire connection to the SPMNS
- Mounting plate is black and measures, 8 3/4" x 5 1/4", fits into a 4 gang back box
- All output circuitry is Power Limited

Table 1. Inputs: Audio & Activation

Priority Ordered Inputs	Priority Level	Type of Input
Auxiliary Microphone	1	MNS Microphone
Digital Message Input 1	2	
Digital Message Input 2	3	
Digital Message Input 3	4	Contact Closure activation
Digital Message Input 4	5	
Digital Message Input 5	6	
Onboard Microphone	7	Fire Microphone
Digital Message Input 6	8	
Digital Message Input 7	9	Contact Closure activation
Digital Message Input 8	10	

Table 2. Inputs: Audio/Technical Specifications

Switch mode, Class D amplifier (40 Watts)	
Speaker Outputs	25V or 70.7V power limited
Frequency Response	Voice: 275 Hz – 6.5 kHz Meets UL Voice Evacuation Requirements of 800–2800 Hz
Signal-to-Noise Ratio	Better than 65 dB
Dynamic Range	Better than 65 dB
Total Harmonic Distortion	Less than 2%
Stand by Current Draw	130 mA
Alarm Current Draw	4.7 amps

Table 3. SPMNS Mechanical

Dimensions	21" H x 16" W x 6" D (wall mount)
Weight	36 lbs. (without batteries)
Finish	Red or black exterior enclosure
Door Lock	Wheelock key-lock



Table 4. Ordering Information

Model Number	Description
SPMNS	In-Building Mass Notification, Messaging, and Emergency Voice Evacuation System with 24 VDC battery backup circuitry. Single channel system with 40 watts of supervised audio power and 2 amps of supervised 24 VDC synchronized strobe power and 8 standard message. (Batteries not included, 2 required) red enclosure
SPMNS-MIC	Mass Notification Microphone for use with the SPMNS, black plate
PS-8-LP	8 Amp Supervised Remote Power Supply, 24VDC
BATC-R	Battery Cabinet, Red
BATC-B ^a	Battery Cabinet, Black
BAT-1224	12 Volt, 24Ampere Battery Cell

^a For additional information, please refer to the PS-8-LP specification sheet, TD450003EN.

Table 5. Message Capabilities


Message and Priority #	Type of Message	Voice Type	Message Script
1	MNS	Male	Three (3) seconds of 1kHz of tone (followed by): ATTENTION: There is an emergency in the building. Evacuate the building in an orderly fashion. Follow all instructions given by emergency responders.
2	MNS	Male	Three (3) seconds of 1kHz of tone (followed by): ATTENTION: A severe weather conditions exist – Seek shelter immediately until further notice.
3	MNS	Male	Three (3) rounds seconds of 1kHz of tone (followed by): ATTENTION: Hazardous Material Warning; Shut down all heating, ventilation, and air conditioning systems; Seek cover immediately away from doors and windows. Stay where you are until contacted by local authorities.
4	MNS	Female	ATTENTION: The building emergency has ended. An all clear has been given. Please resume normal activities.
5	MNS	Female	ATTENTION: There is an on-going situation in the building. Please listen for further announcements and remain safe until further notice.
6	Fire	Male	May I have your attention please! A fire emergency has been reported in the building. While this is being verified, please leave the building by the nearest exit. Do not use the elevators.
7	Fire	Male	May I have your attention please! A fire emergency has been reported in the building. While this is being verified, please leave the building by the nearest exit. Do not use the elevators.
8	Fire	Male	Five (5) seconds of 1kHz tone (followed by). May I have your attention please! This is a test of the Mass Notification System, repeat, this is only a test

- Each message can be selected to have a code 3 pre-alert tone, a 1kHz continuous pre-alert tone, or no pre-alert tone
- Post-tones are also selectable and match the pre-tones for individual messages
- Any of the 8 messages are field programmable to record your own custom message
 - Each message length is 30 seconds
 - A 1/8" line level audio input jack is supplied for message recording
 - A two-step recording procedure is required to ensure and verify that the standard message will be permanently erased
- Factory programmed messages are available for custom messages
 - Contact customer service for additional information
 - Form is required and can be downloaded from Eaton.com/massnotification

SAFEPATH 2-Zone Class A or 4-Zone Class B Speaker Audio Splitter

Description

- Supervised 2-zone Class A or 4-zone Class B speaker audio splitter for the SP40S, SP40/2 or audio boosters
- Enables a single supervised speaker audio output to drive up to two Class A supervised speaker audio outputs or four Class B supervised speaker audio outputs
- For operation with SAFEPATH family of products: SPMNS, SP40S, SP40/2, SPB-320, SPB-160, SPB-80/4



Features

- Expands one zone to up to 2 zones of supervised speaker audio output in Class A
- Expands one zone to up to 4 zones of supervised speaker audio output in Class B
- Each Class A zone can accept up to 40 watts of audio
- Each Class B zone can accept up to 40 watts of audio
- Operates on either 25V or 70.7V RMS
- Mounts inside the enclosure of the SP40S, SP40/2 or

- audio boosters
- Power and Trouble LEDs
- Individual zone short and open LED indication
- Capable of detecting wiring faults
- Removable wiring terminals for quick connect/disconnect accepting 12–22 AWG
- All output circuitry is Power Limited
- Space provided to allow for naming of the zones
- Powered by 24VDC, supplied by either the SP40S, SP40/2 or audio boosters
- Standby and Alarm current at 24VDC is 15mA

Approvals & compliances

- UL Standard 864, 9th edition, and California State Fire Marshal (CSFM), New York City (MEA)
- UFC 04-021-01 2002

Applications

- Provides for expansion of one zone to up to 2 zones of supervised speaker audio output in Class A
- Provides for expansion of one zone to up to 4 zones of supervised speaker audio output in Class B

Table 6. Ordering Information

Model Number	Order Code	Description
SP4Z-A/B	9900	Supervised 2-Zone Class A or 4-Zone Class B Speaker Audio Splitter for the SP40S, SP40/2 or Audio Boosters
SPMB4Z	9907	Mounting Bracket for the SP4Z-A/B is required when used with the Audio Boosters

Note: The Speaker Splitter Mounting Bracket (SPMB4Z) is required when the speaker splitter is used in audio boosters. The SPMB4Z can support two splitters.

SAFEPath Audio Boosters

Description

Supervised Facility Communication and Emergency Voice Evacuation Audio and Audio/Strobe Power Boosters, UL 2572 for MNS, UL Standard 1711 and UL Standard 864, 9th edition with 24VDC battery backup capabilities. Designed to provide for additional supervised audio power for live voice or pre-recorded messages. Fully supervised patent pending circuitry is always in effect. The SPB-80/4 also provides 4 Amps of 24 VDC Supervised and Synchronized Strobe Power.

The SPB-320, SPB-160 and the SPB-80/4 easily connects to the Eaton SPMNS. Multiple SPB-320, SPB-160 and SPB-80/4 Audio Boosters can be inter-connected to accommodate large installations with supervised audio power and also supervised and synchronized strobe power requirements.

The SPB-320 draws 2.4 watts of audio input power to properly operate and provide additional supervised audio output power. The SPB-160 and the SPB-80/4 draws 1.2 watts of audio input power to properly operate and provide additional supervised audio output power. A maximum of 5,280 watts of supervised audio power can be achieved. Additional strobe power can be obtained via a combination of SPB-80/4 or Wheelock Power Supplies/Chargers.



- SPB-320:** 320 watt supervised audio power
- SPB-160:** 160 watt supervised audio power booster (two 80-watt circuits)
- SPB-80/4:** 80 watt supervised audio power booster with 4 amps of supervised and synchronizable strobe power (two 2 amp circuits)

Features

System Activation: Audio

- 70V or 25V input from the SPMNS
- 1 Volt input from SP4-RMX

System Activation: Strobe (SPB-80/4)

- 8–33VDC NAC input connected to the strobe input

Power supply & batteries

- Fully supervised patent pending circuitry always in effect
- Power limited circuitry
- Class D amplifiers

- Internal battery charger and power supply
- Required batteries fit inside the enclosure (sold separately)
- SPB-320 requires four 12 VDC, 12 AH batteries
- SPB-160 and SPB-80/4 require two 12 VDC, 12 AH batteries

Inputs:

- Audio speaker inputs: 70V or 25V, field selectable
- Auxiliary in (for alarm input signal)

Outputs:

- SPB-320 has four 80 watt speaker output circuits
- SPB-160 has two 80 watt speaker output circuits
- SPB-80/4 has one 80 watt speaker output circuit and two 2 amp strobe circuits (4 amps total)
- Supervised Audio Speaker outputs: 70V or 25V field selectable (all boosters must be either 70 V or 25 V)
- Expansion output (supervised, 24VDC at 0.5A in alarm condition) used for connecting multiple boosters
- DC output (unsupervised for optional splitter power). Each speaker circuit (four for the SPB-320, two for the SPB-160, one for the SPB-80/4) can connect to speaker splitters.

SPB-80/4 Strobe Features:

- Two 24VDC 2 amps, NAC supervised, synchronizable, power limited, Class B strobe outputs
- Selectable outputs; Wheelock sync, pass through, or constant DC
- Trouble LED for open and short output conditions
- Alarm indicator: LED for strobe and expansion outputs

Approvals & compliances

- UL 2572 for MNS, UL Standard 864, 9th edition, UL Standard 1711, California State Fire Marshal (CSFM), New York City (MEA)
- OSHA 1910.165, ADA and UFC 04-021-01 Compliant
- 1 Year Warranty

Applications

- Provides for additional supervised audio power for large installations
- Provides for additional supervised and synchronizable strobe power for large installations
- Can be used in new construction as well as in retrofit construction

Technical specifications:

- 120VAC, 3.8A, 60 Hz input
- SP40SE Models 240 VAC, 2.5A, 50–60 Hz
- Standby current draw: 120mA, per amplifier board
- Alarm current draw: 9 amps, per amplifier board
- SPB-80/4 and SPB-160 have one amplifier board
- SPB-320 has two amplifier boards
- System Frequency Response:
 - Voice: 400 Hz–6.5 kHz
- Removable quick connect/disconnect terminals, accepts 12–22 AWG
- Multiple LEDs for easy indication of system diagnostic conditions

- Signal-to-Noise Ratio: > 70 dB
- Dynamic Range: > 65 dB
- Total Harmonic Distortion: 2%

Table 7. Mechanical

SPB-160, SPB-80/4	
Dimensions	21" H x 16" W x 6" D (wall mount)
Weight	36 lbs. (without batteries)
Finish	Red exterior enclosure
Door Lock	Wheelock key-lock
SPB-320	
Dimensions	36" H x 24" W x 6" D (wall mount)
Weight	80 lbs. (without batteries)
Finish	Red or black exterior enclosure
Door Lock	Wheelock key-lock

Table 8. Ordering Information

Model Number	Order Code	Description
SPB-320	9918	320 watt supervised audio power booster (Four 80-watt circuits)
SPB-320E	6336	320 watt supervised audio power booster (four 80 watt circuits), 220 VAC input
SPB-320E-B	6353	320 watt supervised audio power booster (four 80 watt circuits), 220 VAC input, black enclosure
SPB-160	8989	160 watt supervised audio power booster (two 80 watt circuits), red enclosure
SPB-160-B	9930	160 watt supervised audio power booster (two 80 watt circuits), black enclosure
SPB-160E	6149	160 watt supervised audio power booster (two 80 watt circuits), 220 VAC input
SPB-160E-B	6150	160 watt supervised audio power booster (two 80 watt circuits), 220 VAC input, black enclosure
SPB-80/4	8988	80 watt supervised audio power booster with 4 amps of supervised and synchronized strobe power (two 2 amp circuits), red enclosure
SPB-80/4-B	9931	80 watt supervised audio power booster with 4 amps of supervised and synchronized strobe power (two 2 amp circuits), black enclosure
SPB-80/4E	6147	80 watt supervised audio power booster with 4 amps of supervised and synchronized strobe power (two 2 amp circuits), 220 VAC input
SPB-80/4E-B	6148	80 watt supervised audio power booster with 4 amps of supervised and synchronized strobe power (two 2 amp circuits), 220 VAC input, black enclosure
SPMB4Z	9907	Speaker splitter mounting bracket for SPB-320, SPB-160 or SPB-80/4

Note: The Speaker Splitter Mounting Bracket (SPMB4Z) is required when the speaker splitter is used in audio boosters. The SPMB4Z can support two splitters.

Architects and engineers specifications

SAFEPath Mass Notification System

The system shall be a multi-purpose NFPA compliant, supervised, fire/emergency communications system and shall interface with a building fire alarm system (FAS) to provide a complete In-Building MNS. The system shall control all audio and visual notification appliances for both fire and MNS and report trouble and supervisory signal through the FAS. The system shall be capable of delivering 40 watts of supervised audio power and 2 amps of supervised 24 VDC synchronized strobe power. Minimum supervised audio power shall be 40 watts, expandable to 5280 watts, depending on system configuration and with additional modules and power boosters. Supervised 24 VDC synchronized strobe power shall be 2 amps, expandable to the requirements of the installation. The system shall be capable of operating from a 120 VAC power source. SPMNS shall be capable of operating from a 240 VAC power source. All models shall have a 24 VDC battery backup. Standard on-board system features shall include: digital voice messaging, a hand-held push-to-talk microphone with override priority, and a power supply/battery charger. Form C contacts shall be provided for system alarm and trouble conditions.

The system shall have 8 message contacts with contact closure activation. The system shall have 10 priority ordered inputs, including: On Board Microphone, Auxiliary Input (Line Level), and 8 Digital Messages. The system shall have preset audio levels for emergency messaging (prerecorded and live microphone). The system shall be supplied with 8 pre-recorded messages and be capable of in-field recording of customer unique messages. The system shall have a dual-tone tone generator with Code-3 Tone and Slow Whoop.

The panel shall have power-limited circuitry with an internal battery charger and power supply. The power supply/charger section shall be able to charge 24 VDC batteries with a maximum capacity of 33 amp hours. Up to two 12 VDC, 12 AH batteries may be housed in the enclosure. Batteries larger than 12 Ah shall be housed in a separate enclosure such as the Cooper Wheelock BATC or equivalent. Batteries shall be supplied separately.

The system shall have power limited circuitry and class B wiring. Wiring terminal blocks will be removable and accept #22 - #12 AWG wire. Audio output voltage shall be selectable for 25V or 70.7V. The voice (live microphone or recorded message) frequency response shall be 275 Hz – 6.5 kHz. Stand by current draw shall be 140mA. Alarm current draw shall be 4.7 amps. The signal to noise ratio shall be better than 65 dB, dynamic range shall be better than 65 dB, total harmonic distortion shall be less than 2%.

The system shall be wall mountable, enclosed in a steel locking enclosure. The required batteries for 40-watt systems shall fit inside the enclosure. The 40 watt system shall weigh no more than 36 lbs (without batteries) and its dimensions shall not exceed 21" H x 16" W x 6" D. Approvals for the system shall include: UL Standard 864, 9th edition, UL 2572 for MNS, and UL Standard 1711. The system shall be OSHA 1910.165, and ADA compliant. 1 Year Warranty.

SPMNS Microphone

The Mass Notification Microphone shall be UL 2572 for MNS, UL Standard 864, 9th edition and California State Fire Marshal (CSFM) approved for use with the Mass Notification System.

The Mass Notification Microphone shall be a supervised microphone used for live voice emergency communication messages. When used with the SAFEPath Mass Notification System, the Mass Notification Microphone shall have the capability to override the fire microphone and any fire pre-recorded messages. All output circuitry shall be power limited. Multiple on board diagnostic LED indicators shall be provided. All wiring shall be capable of accepting 12 – 22 AWG wiring.

SAFEPath Audio Boosters

The Wheelock SPB-320, SPB-160 and SPB-80/4 Audio Boosters shall be NFPA compliant supervised audio and supervised 24VDC synchronized strobe power boosters (some models will have supervised 24VDC synchronized strobe booster capability). The booster shall have 24VDC battery backup capabilities. The booster shall have the capability to be inter-connected to accommodate large installations with supervised audio power and also supervised and synchronized strobe power requirements. Three versions of the booster shall be made available: SPB-80/4, (80 watts of supervised audio power and 4 amps of supervised and synchronized strobe power), SPB-160 (160 watts of supervised audio) or SPB-320 (320 watts of supervised audio).

Each booster shall use 1.2 watts of audio input power (The SPB-320 requires 2.4 watts of audio power) to properly operate and provide additional supervised audio output power. A combination of boosters can be added together to provide for a maximum of 5,280 watts of supervised audio power. Additional strobe power can be obtained via a combination of boosters. The audio section of the booster shall be connected via a selectable 70V or 25V input from the Cooper Notification SPMNS. The strobe section of the booster shall be divided into two sections each supplying two Amps of 24VDC, NAC, supervised, synchronizable, power limited, Class B strobe outputs, with selectable outputs offering Wheelock sync, pass through, or constant DC and can be activated via 8-33VDC NAC input or contact closure.

The internal battery charger/power supply shall be capable of charging 24 VDC batteries with a maximum capacity of 33 amp hours. The enclosure shall be capable of housing the correct number of 12 VDC rechargeable batteries (SPB-80/4 (2), SPB-160 (2), SPB-320 (4)) with a maximum capacity of 12 Amp hours. Batteries with a larger capacity require an external battery enclosure(s) such as the Cooper Notification BATC or equivalent.

The boosters shall have power-limited circuitry and be a class D amplifier with an internal battery charger and power supply. The required batteries (purchased separately) shall fit inside the enclosure (two 12VDC, 12 AH for the SPB-80/4 or SPB-160 and four 12 VDC, 12 AH for the SPB-320). The booster shall operate on 120VAC, 3.8A, 50 – 60 Hz input. E model boosters shall operate on 240 VAC, 2.5A, 50 – 60 Hz input. The SPB-80/4 or SPB-160 standby current draw shall be 120mA and alarm current draw shall be 9 Amps. The SPB-320 consists of two SPB-160's. Each SPB-160 shall have its own power supply and battery charger. The voice frequency response shall be 400 Hz – 6.5 kHz +/- 3 dB. Removable quick connect/disconnect terminals that accept 12 -22 AWG shall be used. Multiple LED's for easy indication of system diagnostic conditions shall be present on the PC board. The Signal to Noise Ratio shall be > 70 dB, the dynamic range shall be > 65 dB, the Total Harmonic Distortion spec shall be 2%.

Effective January 2018

The booster shall be wall mountable, enclosed in a steel locking enclosure, with a red finish. Approvals for the booster shall include: UL 2572 for MNS, UL Standard 864, 9th edition, UL Standard 1711, CSFM and MEA. The system shall be OSHA 1910.165, ADA and UFC 04-021-01 2002 (including October 2007 Draft) compliant. The booster shall carry a 1 Year Warranty.

The SPB-80/4 & SPB-160 enclosure dimensions are 21" H x 16" W x 6" D and the SPB-320 enclosure dimensions are 36" H x 24" W x 6" D.

4 Zone Class B Speaker Splitter

The Wheelock SP4Z-A/B shall be UL 2572 for MNS, UL Standard 864, 9th edition, California State Fire Marshal (CSFM) and New York City (MEA) approved, 2-Zone Class A or 4-Zone Class B Speaker Splitter for operation with the SPMNS, SP40/2, SPB-80/4, SPB-160 and SPB-320. The SP4Z-A/B shall enable a single supervised speaker audio output to drive up to two Class A supervised speaker audio outputs or four Class B supervised speaker audio outputs. Each Class A zone shall be capable of accepting up to 40 watts and operate on either 25 or 70.7V RMS of audio input. Each Class B zone shall be capable of accepting up to 40 watts of audio and operate on either 25 or 70.7V RMS of audio input. The SP4Z-A/B shall be capable of supporting live microphone and prerecorded emergency voice evacuation messages.

The SP4Z-A/B shall mount inside the enclosure of the SPMNS, SP40/2, SPB-80/4, SPB-160 and SPB-320 and shall have power and trouble LED with individual zone short and open LED indication. The SP4Z-A/B shall be capable of detecting wiring faults. The SP4Z-A/B shall be powered by 24VDC, which is to be supplied by the SPMNS, SP40/2, SPB-80/4, SPB-160 or SPB-320. Standby and Alarm current at 24VDC shall be 15mA. Removable wiring terminals for quick connect/disconnect accepting 12–22 AWG shall be incorporated. All output circuitry shall be power limited. Space shall be provided to allow for naming of the zones.

①

Note: Due to continuous development of our products, specifications and offerings are subject to change without notice in accordance with Eaton's Cooper Notification business standard terms and conditions.

Note: Refer to the products Installation Instructions for proper installation, wiring procedures and any additional specifications.



WE ENCOURAGE AND SUPPORT NICET CERTIFICATION

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
Eaton.com

Eaton
Life safety & mass notification solutions
273 Branchport Ave.
Long Branch, NJ 07740
www.eaton.com/massnotification

© 2018 Eaton
All Rights Reserved
Printed in USA
Publication No. TD450143EN
January 2018

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

