

# Transformers

## AC - Power

### 88 Series

Edwards 88 Series Power Transformers provide low voltage source from 50 to 250 volt amps for all large signaling installations.

Holes are provided in transformer housing for surface mounting.

### Features and Specifications

- Enclosed connections
- Primary Pigtails
- Screw terminal connections on secondary



### Ordering Information

Description	Cat. No.	Primary Voltage <sup>1</sup>	Secondary	
			Volts	VA
Power Transformers	88-50	120V AC	24V AC	50
			12V AC	25
	88-Y50	240V AC	24V AC	50
			12V AC	25
	88-100	120V AC	24V AC	100
			12V AC	50
	88-Y100	240V AC	24V AC	100
			12V AC	50
	88-250A	120V AC	24V AC	250
			20V AC	200
			16V AC	160
			12V AC	125
8V AC			80	
4V AC			40	

<sup>1</sup>AC voltage frequency is 50/60 Hz



# Transformers

## AC - Power

### 88 Series

#### Weights and Dimensions

Cat. No.	Approx. Net Weight (lb.)	Approx. Shipping Weight (lb.)	Dimensions	
			A (in.)	B (in.)
88-50	1.94	4.30	5 1/2	4 3/8
88-Y50	2.05	4.40	5 1/2	4 3/8
88-100	2.60	5.70	5 15/16	4 11/16
88-Y100	2.30	5.40	5 15/16	4 11/16
88-250A	12	12.5	6.8	4.1

