



General Purpose

The Power of a Perfect Fit

Interstate's SLA battery family powers more than devices. They empower the people who use them—and choose them.

Part #	Volts	Ah Capacity*	Dimensions				Terminal
			L	W	H	TH	
SLA0826	4V	4.5 Ah	1.89	2.07	3.70	3.94	F1
SLA0833	4V	8 Ah	3.58	1.97	3.98	3.98	F2
SLA0836	4V	10 Ah	4.02	1.97	3.70	3.94	F2
SLA0855	6V	1.1 Ah	2.01	1.65	2.01	2.24	F1
SLA0865	6V	1.2 Ah	3.82	0.98	2.05	2.24	F1
SLA0184	6V	2.0 Ah	1.69	1.46	2.99	2.99	F1
SLA0902	6V	2.8 Ah	2.60	1.30	3.82	4.06	F1
SLA0885	6V	3.2 Ah	5.28	1.34	2.36	2.60	F1
SLA0905	6V	4.5 Ah	2.76	1.85	4.02	4.17	F1
SLA0906	6V	5 Ah	2.64	2.64	3.78	3.98	F1
SLA0916	6V	5 Ah	2.64	2.64	3.82	4.65	SPR
SLA0935	6V	7 Ah	3.86	2.20	4.02	4.02	F1
SLA0925	6V	7 Ah	5.94	1.34	3.70	3.94	F1
SLA0945	6V	9 Ah	3.86	2.20	4.65	4.72	F1
SLA0955	6V	10 Ah	5.94	1.97	3.70	3.90	F1
SLA0959	6V	12 Ah	5.94	1.97	3.70	3.90	F2
SLA0961	6V	12 Ah	5.94	1.97	3.70	3.90	F1
SLA0986	6V	20 Ah	6.18	3.27	4.92	4.92	NB
SLA0993	6V	42 Ah	6.38	3.46	6.42	6.69	F2
SLA0994	6V	42 Ah	6.38	3.46	6.42	6.85	NB
SLA0988	8V	3.2 Ah	5.28	1.42	2.48	2.72	F1
SLA1000	12V	700 mAh	3.78	0.98	2.44	2.44	Plug
SLA1005	12V	1.3 Ah	3.82	1.69	2.09	2.28	F1
SLA0218	12V	2 Ah	2.76	1.89	3.86	4.09	F1
SLA1020	12V	2 Ah	5.91	0.79	3.54	3.54	F1

Part #	Volts	Ah Capacity*	Dimensions				Terminal
			L	W	H	TH	
SLA1016	12V	2.3 Ah	7.01	1.38	2.36	2.60	F1
SLA1015	12V	2.3 Ah	7.01	1.34	2.36	2.36	F1
SLA1022	12V	2.9 Ah	3.11	2.20	3.90	4.21	F1
SLA0077	12V	2.9 Ah	3.11	2.20	3.90	4.13	F1
SLA1042	12V	3 Ah	5.28	2.64	2.36	2.60	F2
SLA1035	12V	3.5 Ah	5.28	2.64	2.36	2.60	F1
SLA1041	12V	3.5 Ah	5.28	2.64	2.36	2.60	F1
SLA1055	12V	5 Ah	3.54	2.76	3.98	4.21	F1
SLA1056	12V	5 Ah	3.54	2.76	3.94	4.21	F2
SLA1075	12V	8 Ah	5.94	2.56	3.70	3.94	F1
SLA1079	12V	8 Ah	5.94	2.56	3.70	3.94	F2
SLA1080	12V	7.5 Ah	5.94	2.56	3.70	3.90	F2
SLA1097	12V	10 Ah	5.94	2.56	4.37	4.61	F2
SLA1104	12V	12 Ah	5.94	3.86	3.66	3.86	F2
SLA1105	12V	12 Ah	5.94	3.86	3.66	3.86	F1
SLA1098	12V	12 Ah	5.94	3.86	3.66	4.09	NB
SLA1116	12V	18 Ah	7.13	2.99	6.57	6.57	NB
SLA1115	12V	18 Ah	7.13	2.99	6.57	6.57	F2
SLA1146	12V	26 Ah	6.50	6.89	4.88	4.88	NB
SLA1150	12V	30 Ah	6.50	4.88	6.89	6.89	NB
SLA1156	12V	35 Ah	7.72	5.12	6.22	6.65	INS
SLA1155	12V	35 Ah	7.76	5.16	6.26	7.09	Flag
SLA1161	12V	44 Ah	7.76	6.50	6.69	6.69	INS
SLA1165	12V	55 Ah	9.02	5.43	8.07	8.90	Flag
SLA1160	12V	55 Ah	9.02	5.43	8.27	9.25	NB - Reversed
SLA1180	12V	65 Ah	13.70	6.61	7.01	7.01	INS
SLA1175	12V	75 Ah	10.20	6.61	8.35	8.98	Flag
SLA1185	12V	100 Ah	12.09	6.61	8.19	9.06	Flag
SLA1189	12V	100 Ah	12.09	6.61	8.19	8.43	INS