Farenhyt

Description

The IFP-2000 network repeater modules are used when panels to be networked are located further than 20 feet apart or when panels are located in multiple buildings.

The IFP-RPT is available for use in two versions:

- IFP-RPT-FO
- IFP-RPT-UTP

The IFP-RPT-UTP repeater is used to network panels using twisted pair copper wiring.

The IFP-RPT-FO repeater is used to network panels using either multimode 62.5/125 micron fiber optic cable or twisted pair copper wiring.

Installation

Due to the physical size of the repeaters it is difficult to mount them directly in the IFP-2000 cabinet. Accessory kits for the repeaters are available that include a small cabinet with door, key, mounting hardware, five foot ribbon cable to connect the repeater to the control panel and the repeater printed circuit board.

For specific installation instructions refer to the IFP-2000 installation manual part number 151430.

The accessory kit part numbers are:

IFP-RPT-UTP-KIT - Wired twisted pair network repeater card and cabinet kit.

IFP-RPT-FO-KIT- Fiber optic network repeater card and cabinet kit.

Specifications

Operating voltage 24VDC (provided from IFP-2000)

Operating Current: 0.013 amp

Operating Temperature: 32° to 120° F (0° to 49° C)

Relative Humidity: 0 to 93% RH, non-condensing





Network Repeater

Features

- Listed under UL 864 9th Edition
- Supports BUS or class A (style 7) wiring topologies

Ordering Information

| IFP-RPT-UTP | Wired twisted pair network repeater card |
|-----------------|--|
| IFP-RPT-FO | Fiber optic network repeater card |
| IFP-RPT-UTP-KIT | Wired twisted pair network repeater card and cabinet kit |
| IFP-RPT-FO-KIT | Fiber optic network repeater card and cabinet kit |



This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific application or anticipate all requirements. All specifications are subject to change without notice. For more information contact Silent Knight 7550 Meridian Circle, Suite 100, Maple Grove, MN 55369-4927 Phone: (800) 328-0103, fax (763) 493-6475 www.Farenhyt.com

P/N 350403 Rev A © Honeywell International Inc.

firealarmresources.com