



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

MGC's Remote Fire Fighter's Telephones are designed to function as a remote emergency telephone for the QX-5000 Emergency Zoned Audio System or the Flex-Net™ system. The remote telephone is made up of the chassis Model FT-300A, the backbox BB-330, a flush mount cover TC-330 and a surface mount cover TC-331. These units are made to be use as an emergency telephone to call the QMT-5300A Fire Fighters' Master Telephone or the QMT-5302N or QMT-5302NV Fire Fighters' Master Telephone.

MECHANICAL INSTALLATION

1. Back box BB-330 can be installed either flush (recess) or surface mount as desired.
2. Use front cover plate TC-330 for flush mount application.
3. Use front cover plate TC-331 for surface mount application.
4. Wire the unit as shown in wiring diagram below.
5. Mount the handset chassis assembly (FT-300A) into backbox with three screws supplied. Use the outer three mounting holes.
6. Mount the front cover plate into the backbox with four screws supplied. Use inner four mounting holes.
7. Install break glass by gently sliding it up from inside through the top mounting bracket then slide down the glass in place.
8. Lock door using the key supplied. Keep keys on safe place for future use.

OPERATION

1. In the event of an emergency situation, the user must break the "break glass" to access the telephone handset in order to place a call to the QMT-5300A Fire Fighters' Master Telephone (usually situated in the lobby area). When the handset is lifted, the green Incoming LED on the QMT-5300A will flash and the buzzer will sound indicating an emergency call is on line.
2. The fireman at the QMT-5300A Fire Fighters' Master Telephone will then be able to communicate with the caller by simply selecting the appropriate zone (visible flashing LED at the QZT-5302) and pushing the button next to the flashing LED to engage communication.
3. To end communication, simply hang up the handset.

LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

MGC's Remote Fire Fighter's Telephones are designed to function as a remote emergency telephone for the QX-5000 Emergency Zoned Audio System or the Flex-Net™ system. The remote telephone is made up of the chassis Model FT-300A, the backbox BB-330, a flush mount cover TC-330 and a surface mount cover TC-331. These units are made to be use as an emergency telephone to call the QMT-5300A Fire Fighters' Master Telephone or the QMT-5302N or QMT-5302NV Fire Fighters' Master Telephone.

MECHANICAL INSTALLATION

1. Back box BB-330 can be installed either flush (recess) or surface mount as desired.
2. Use front cover plate TC-330 for flush mount application.
3. Use front cover plate TC-331 for surface mount application.
4. Wire the unit as shown in wiring diagram below.
5. Mount the handset chassis assembly (FT-300A) into backbox with three screws supplied. Use the outer three mounting holes.
6. Mount the front cover plate into the backbox with four screws supplied. Use inner four mounting holes.
7. Install break glass by gently sliding it up from inside through the top mounting bracket then slide down the glass in place.
8. Lock door using the key supplied. Keep keys on safe place for future use.

OPERATION

1. In the event of an emergency situation, the user must break the "break glass" to access the telephone handset in order to place a call to the QMT-5300A Fire Fighters' Master Telephone (usually situated in the lobby area). When the handset is lifted, the green Incoming LED on the QMT-5300A will flash and the buzzer will sound indicating an emergency call is on line.
2. The fireman at the QMT-5300A Fire Fighters' Master Telephone will then be able to communicate with the caller by simply selecting the appropriate zone (visible flashing LED at the QZT-5302) and pushing the button next to the flashing LED to engage communication.
3. To end communication, simply hang up the handset.

LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

MGC's Remote Fire Fighter's Telephones are designed to function as a remote emergency telephone for the QX-5000 Emergency Zoned Audio System or the Flex-Net™ system. The remote telephone is made up of the chassis Model FT-300A, the backbox BB-330, a flush mount cover TC-330 and a surface mount cover TC-331. These units are made to be use as an emergency telephone to call the QMT-5300A Fire Fighters' Master Telephone or the QMT-5302N or QMT-5302NV Fire Fighters' Master Telephone.

MECHANICAL INSTALLATION

1. Back box BB-330 can be installed either flush (recess) or surface mount as desired.
2. Use front cover plate TC-330 for flush mount application.
3. Use front cover plate TC-331 for surface mount application.
4. Wire the unit as shown in wiring diagram below.
5. Mount the handset chassis assembly (FT-300A) into backbox with three screws supplied. Use the outer three mounting holes.
6. Mount the front cover plate into the backbox with four screws supplied. Use inner four mounting holes.
7. Install break glass by gently sliding it up from inside through the top mounting bracket then slide down the glass in place.
8. Lock door using the key supplied. Keep keys on safe place for future use.

OPERATION

1. In the event of an emergency situation, the user must break the "break glass" to access the telephone handset in order to place a call to the QMT-5300A Fire Fighters' Master Telephone (usually situated in the lobby area). When the handset is lifted, the green Incoming LED on the QMT-5300A will flash and the buzzer will sound indicating an emergency call is on line.
2. The fireman at the QMT-5300A Fire Fighters' Master Telephone will then be able to communicate with the caller by simply selecting the appropriate zone (visible flashing LED at the QZT-5302) and pushing the button next to the flashing LED to engage communication.
3. To end communication, simply hang up the handset.

LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

MGC's Remote Fire Fighter's Telephones are designed to function as a remote emergency telephone for the QX-5000 Emergency Zoned Audio System or the Flex-Net™ system. The remote telephone is made up of the chassis Model FT-300A, the backbox BB-330, a flush mount cover TC-330 and a surface mount cover TC-331. These units are made to be use as an emergency telephone to call the QMT-5300A Fire Fighters' Master Telephone or the QMT-5302N or QMT-5302NV Fire Fighters' Master Telephone.

MECHANICAL INSTALLATION

1. Back box BB-330 can be installed either flush (recess) or surface mount as desired.
2. Use front cover plate TC-330 for flush mount application.
3. Use front cover plate TC-331 for surface mount application.
4. Wire the unit as shown in wiring diagram below.
5. Mount the handset chassis assembly (FT-300A) into backbox with three screws supplied. Use the outer three mounting holes.
6. Mount the front cover plate into the backbox with four screws supplied. Use inner four mounting holes.
7. Install break glass by gently sliding it up from inside through the top mounting bracket then slide down the glass in place.
8. Lock door using the key supplied. Keep keys on safe place for future use.

OPERATION

1. In the event of an emergency situation, the user must break the "break glass" to access the telephone handset in order to place a call to the QMT-5300A Fire Fighters' Master Telephone (usually situated in the lobby area). When the handset is lifted, the green Incoming LED on the QMT-5300A will flash and the buzzer will sound indicating an emergency call is on line.
2. The fireman at the QMT-5300A Fire Fighters' Master Telephone will then be able to communicate with the caller by simply selecting the appropriate zone (visible flashing LED at the QZT-5302) and pushing the button next to the flashing LED to engage communication.
3. To end communication, simply hang up the handset.

LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

WIRING



LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

WIRING



LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

WIRING



LT-434 Rev.5 October 2017



FT-300A, TC-331, TC-330 REMOTE FIRE FIGHTERS' TELEPHONE INSTALLATION INSTRUCTIONS

WIRING



LT-434 Rev.5 October 2017