


Functional Devices, Inc. 101 Commerce Drive Sharpsville, IN 46068 Confidence & Peace of Mind in Every Box™


Office: (765) 883-5538 Toll Free: (800) 888-5538 www.functionaldevices.com sales@functionaldevices.com

## **CURRENT TRANSFORMER**

## CT-05A0-333

Enclosed Self-Powered Split Core 5 Amp Current Transformer with 333 mV Output













## **SPECIFICATIONS**

**Environment:** Indoor Use Only 5 to 176° F (-15 to 80°C)

90% relative humidity

Wires: 6', 22 AWG

600V Rated

Primary Input (A): 60A max. AC 50/60 Hz

Secondary Output (V): 0.333 Vac

Accuracy: 0.3% (typical)

Linearity: 10%-120%
Polarity: White-Hi, Black-Low

Frequency Range: 40-400 Hz Max Sense Voltage: 600 Vac

**Approvals:** ETL Listed, CE, RoHS

**Ratio:** 5A/0.333V

Alternate ratios available

for large orders