

Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 | Office: (765) 883-5538 | Fax: (765) 883-7505

## **ACTRANSDUCERS**

## **RIBXG420 Series**

Current Transducers, Split Core, Up to 100 Amps Sensing Range, 4-20 mA Wire Lead Sensor Output

















## **SPECIFICATIONS**

Operating Temperature:  $-30 \text{ to } 140^{\circ} \text{ F}$ 

**Humidity Range:** 5 to 95% (noncondensing)

Wires: Red (positive) & Black (negative), 16", 18 AWG, 600V Rated

Sensor Type: Internal, with 4-20 mA Transmitter Output

Sensor Range: 0-20 Amps, 0-50 Amps, or 0-100 Amps (See Selection Guide Below)

Accuracy: Refer to chart below. Linearity: 99% FS (20%-100% Span)

Max Output Current: 30 mA Max Sense Voltage: 600 Vac

Approvals: UL Listed, UL508, C-UL, CE, RoHS

Mounting/Installation: Removable mounting tab provided. The wire clamp locks against the wire being

monitored, securing the unit in place.

**Origin:** Made of US and non-US parts

OUTPUT LOAD RESISTANCE	SUPPLY VOLTAGE		
Maximum	Minimum	Maximum	
800 ohms	24 Vdc	35 Vdc	
500 ohms	18 Vdc	35 Vdc	
350 ohms	15 Vdc	35 Vdc	
250 ohms	13 Vdc	35 Vdc	
200 ohms	12 Vdc	35 Vdc	
100 ohms	10 Vdc	35 Vdc	
50 ohms	9 Vdc	35 Vdc	

RIBXG420 SERIES SELECTION GUIDE			ACCURACY		
Model#	Sensing Range	Sensor Output	Span 20% – 100%	Span 10% – 100%	Span 0% – 100%
RIBXG420-20	0-20 Amps	Loop Powered 4-20 mA Transmitter (Pre-Wired)	99%	99%	95%
RIBXG420-50	0-50 Amps	Loop Powered 4-20 mA Transmitter (Pre-Wired)	99%	97.5%	92%
RIBXG420-100	0-100 Amps	Loop Powered 4-20 mA Transmitter (Pre-Wired)	99%	97%	91%

