

Trove1DM1 (Enclosure & Backplane) / TDM1 (Backplane)

Access & Power Integration Solution for DMP



Altronix Trove1DM1 consists of a high-capacity enclosure with removable backplane. This unit easily combines Altronix power/accessories with various combinations of DMP 734 Wiegand Modules in a streamlined package. Trove simplifies board layout and wire management, reducing installation time and labor costs.



Trove1DM1

* Boards not included



Trove1DM1 (Trove1 Enclosure + TDM1 Backplane) TDM1 (Backplane) Features

- Accommodates DMP 734 and 734N Wiegand modules with or without Altronix power/accessories
 - Altronix Power Supplies
 - Altronix Sub-Assemblies
- Includes Altronix Trove1 Enclosure and one (1) removable TDM1 backplane

Agency Listings

UL:

UL294 - Access Control System.

cUL:

CAN/ULC - s319-05 - Electronic Access Control Systems

CE

European Conformity

Features

- Simplifies board layout and wire management
- Convenient knockout configuration:
 - One (1) single knockout
1.948" (1-1/2" Conduit)
 - Nine (9) double knockouts
1.362" (1" Conduit) / 1.115" (3/4" Conduit)

Features (cont'd)

- Accommodates up to two (2) 12VDC/7AH batteries
- 16 AWG powder coated steel
- Includes cam lock, tamper switch and mounting hardware

Trove1DM1 - Dimensions (H x W x D):

Enclosure:

18.0" x 14.5" x 4.625" (457.2mm x 368.3mm x 117.5mm)

Shipping:

21.75" x 18.25" x 5.75" (553mm x 464mm x 146mm)

Trove1DM1 - Weights:

Product - 15.15 lb. (6.87 kg)

Shipping - 19.05 lb. (8.64 kg)

TDM1 - Dimensions (H x W x D):

Backplane:

16.625" x 12.5" x 0.06" (422.3mm x 317.5mm x 1.5mm)

Shipping:

18.0" x 13.75" x 1" (457mm x 350mm x 26mm)

TDM1 - Weights:

Product - 3.35 lb. (1.52 kg)

Shipping - 4.0 lb. (1.81 kg)

All registered trademarks are property of their respective owners.

Access Controller Position Chart for the Following Models:

Altronix / DMP	Pem Mounting
AL400ULXB2, AL400ULXB2V, AL600ULXB, AL600XB220, AL1012ULXB, AL1012XB220, AL1024ULXB2, AL1024XB2V, eFlow4NB, eFlow4NBV, eFlow6NB, eFlow6NBV, eFlow102NB, eFlow102NBV, eFlow104NB, eFlow104NBV, Tango1B	(A)
ACM4, ACM4CB, LINQ8PD, LINQ8PDCB, MOM5, PD4UL, PD4ULCB, PD8UL, PD8ULCB, PDS8, PDS8CB, PDS16, PDS16CB, VR6	(B)
DMP 734 Wiegand Modules	(C)



