


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com **Toll Free:** (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

15 AMP PILOT CONTROL TRACK MOUNT RELAYS


RIBMN12C

Pilot Relay, 15 Amp SPDT, 12 Vac/dc Coil, 2.75" Track Mount



RIBMN12S

Pilot Relay, 15 Amp SPST + Override, 12 Vac/dc Coil, 2.75"Track Mount













SPECIFICATIONS

Relays & Contact Type: One (1) SPDT Continuous Duty Coil (RIBMN12C) One (1) SPST Continuous Duty Coil (RIBMN12S)

Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 6ms

Relay Status: LED On = Activated

Dimensions: 1.10"H x 2.75"W x 0.75"D1/1.25"D2 (RIBMN12C)

1.25"H x 2.75"W x 1.25"D1/1.75"D2 (RIBMN12S)

Housing Detail: See Housing H in housing guide for dimensions

Origin: Made of US and non-US parts

Track Mount: 2.750°

MT212 Mounting Track Sold Separately

Approvals: UL Listed, UL916, C-UL, CE, RoHS

UL864, California State Fire Marshal

Gold Flash: No

Override Switch: No (RIBMN12C); Yes (RIBMN12S)

Contact Ratings:

C300 Pilot Duty

15 Amp General Use @ 125 Vac 10 Amp General Use @ 277 Vac 10 Amp Resistive @ 30 Vdc (N/O) 7 Amp Resistive @ 30 Vdc (N/C) 1/2 HP @ 125 Vac 1 HP @ 250 Vac 1/4 HP @ 277 Vac

Coil Current:

62 mA @ 12 Vac 29 mA @ 11 Vdc 35 mA @ 12 Vdc

Notes: (RIBMN12S)

• Must cut appropriate jumper to select Normally Open or Normally Closed

53 mA @ 10 Vac

Coil Voltage Input:

12 Vac/dc ; 50-60 Hz Drop Out = 2 Vac / 2.5 VdcPull In = 9 Vac / 11 Vdc